

CORRIGENDUM – II TO BIDDING DOCUMENTS FOR

Planning, Design and Construction for Annex and Hostel Buildings for Post Graduate Disciplines at Murshidabad Medical College & Hospital in the State of West Bengal on Turnkey Basis

Bid Reference No.: WBMSCL/NIT- 202/2023

Dated -26.04.2023

1

SI. No.	Page No.	Section	Clause/ Sl. No.		Current Clau	se / Provisio	n		Changed Clau	use / Provisi	on
1	3	Section-1 Notice Inviting e- Tender (e-NIT)	3.	ITB) would for Annex a Disciplines Hospital in Basis" as ex ("BOQ"), following : A. Planning, Annex build B. Construct The other re	The scope of the Selected Bidder (as defined in the ITB) would be "Planning, Design, and Construction for Annex and Hostel Buildings for Post Graduate Disciplines at Murshidabad Medical College & Hospital in the State of West Bengal on Turnkey Basis" as explained in detail in the Bill of Quantities ("BOQ"), which shall chiefly comprise of the following : A. Planning, Design and Construction of a $G + 3$ Annex building B. Construction of a $G+6$ PG Hostel building The other relevant details pertaining to the Project are as follows: -			ITB) would for Annex Disciplines Hospital in Basis" as e ("BOQ"), following : A. Planning Annex build B. Construc The other re as follows:	be "Planning and Hostel Bu at Murshida the State of xplained in der which shall g, Design and ing tion of a G+7 P elevant details p	, Design, and uildings for H bad Medical West Benga tail in the Bill chiefly com Construction PG Hostel buil pertaining to t	College & l on Turnkey of Quantities prise of the of a G + 3 ding he Project are
				Total Bid Security (Rs. in Crores)	Bid Security payable through e – tendering portal (Rs. in Crores)	Bid Security payable by way of Bank Guarantee (Rs. in	Time of Completion (Months)	Total Bid Security (Rs. in Crores) 1.36	Bid Security payable through e – tendering portal (Rs. in Crores) 0.20	Bid Security payable by way of Bank Guarantee (Rs. in Crores) 1.16	Time of Completion (Months) 20 months
				1.36	0.20	<i>Crores)</i> 1.16	20 months	1.50	0.20	1.10	20 months
2	8	Section-1 Notice Inviting e- Tender (e-NIT)	8(iii)(c)	Crores durin, 2018, 2018-2	g last 5 (Five) 2019, 2019-202	financial yea 20, 2020- 202	rs (i.e. 2017- 21 and 2021-	Crores durin 2018, 2018-2	Average Annua g last 5 (Five) 2019, 2019-20. vertified by the) financial yea 20, 2020- 202	urs (i.e. 2017- 21 and 2021-

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
3	24	Section – 2 Instructions to Bidders (ITB)	4.1(c)	Crores during last 5 (Five) financial years (i.e. 2017-2018, 2018-2019, 2019-2020, 2020-2021 and 2021-2022), duly certified by the Chartered Accountant with	"Minimum Average Annual Turnover of Rs. 20.48 Crores during last 5 (Five) financial years (i.e. 2017- 2018, 2018-2019, 2019-2020, 2020-2021 and 2021- 2022), duly certified by the Chartered Accountant with UDIN No."
4	53	Section – 2 Instructions to Bidders ("ITB")	39.1	Contract Price may be given, if requested by the Selected Bidder/Contractor in writing within 30 (thirty) days of the issue of Notification of Award. The Employer shall pay the Mobilisation Advance to the Contractor, in the following 2 tranches, upon completion of the following events :- (a) First tranche of the Mobilisation Advance equivalent to 5% of the Contract Price shall be paid by the Employer, upon completion of the following events/ activities: (i) Construction of labour camp, Contractor's site office and making arrangements for water supply (ii) Construction of the Employers' temporary site office at the site. (iii) Obtaining a Mobilisation Advance Bank Guarantee from a scheduled bank as per form given in Section - 7 (Contract Forms) aggregating to 5% of the Contract Price, being equivalent to the first tranche of the Mobilization Advance, in favour of the Employer and submission of such Bank Guarantee to the Employer. (b) Second tranche of 5% of Mobilisation Advance will be released by the Employer to the Contractor, upon completion of payment by the Employer, of 15% of the total Contract Price and upon the Contractor obtaining a Mobilization Advance Bank Guarantee from a scheduled bank as per form given in Section – 7 (Contract Forms) aggregating to 5% of the Contract Price, being equivalent to the second tranche of the total Contract Price and upon the Contractor obtaining a Mobilization Advance Bank Guarantee from a scheduled bank as per form given in Section – 7 (Contract Forms) aggregating to 5% of the Contract Price, being equivalent to the second tranche of the Mobilisation Advance, in favour of the Employer and	(i) Construction of labour camp, Contractor's site office and making arrangements for water supply (ii) Construction of the Employers' temporary site office

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				Mobilisation Advance shall commence from payment of the Statement first raised after disbursement of first tranche of the Mobilisation Advance and shall been entered as a deduction from Interim Payment (@ 10% of the value of all the Statements paid so far + simple interest @ 10% of the total Mobilisation Advance amount). For subsequent Statements raised by the Contractor, Mobilisation Advance shall be deducted from the interim payment @ 10% of the value of such	If the circumstances are considered reasonable by the Employer, the period mentioned for request by the Contractor in writing for grant of Mobilisation Advance may be extended in the discretion of the Employer. The said Mobilisation Advance Bank Guarantee for advances shall initially be made for the full amount and valid for the Contract period and be kept renewed from time to time to cover the balance amount and likely

SI. No.	Page No.	Section	Clause/ Sl. No.	Curre	ent Clause / Prov	vision	Char	nged Clause / Pro	ovision
5	58	Section – 3 Evaluation and Qualification Criteria ("EQC")	1.2.2	Minimum Average Annual Turnover of INR 68.28 Crores within the last 5 (five) financial years i.e. 2017-2018, 2018-2019, 2019-2020, 2020-2021 and 2021- 2022.	Must meet requirement	Form FIN-2 of Form – 14	Minimum Average Annual Turnover of INR 20.48 Crores within the last 5 (five) financial years i.e. 2017-2018, 2018-2019, 2019-2020, 2020-2021 and 2021- 2022.	Must meet requirement	Form FIN-2 of Form – 14
6	71	Section – 4 Bidding Forms ("BDF")	Form 4 Bid Security Bank Guarantee	"IFS Code: ICIC0001103" "IFS Code: ICIC0001056			956 "		
7	131	Section-5.5 Scope & Specification of Civil Works	4.B.2	architectural des institutions as re any structural minimum 20 yea and which is en metropolitan corp from academic corporation body who does not h Design wing. But fledged in-house from obtaining	ign duly approved ecommended by th and architectural urs of experience mpanelled & regi poration body in In institutions / is required only f have their own in t those who have t Structural Design	e Employer or by firm having a in respective field stered under any dia. This approval any metropolitan for intended bidder house Structural heir exclusive full- wing is exempted any academic	architectural des institutions as re any structural minimum 15 yea and which is en metropolitan corr from academic corporation body who does not h Design wing. Bu fledged in-house from obtaining	ign duly approved ecommended by th and architectural ars of experience mpanelled & regi poration body in In institutions / is required only f have their own in t those who have t Structural Design	wing is exempted any academic
8	131	Section-5.5 Scope & Specification of Civil Works	4.B.4 (c)	"All approach co Highway/State H with storm wate landscaping for	oncrete roads (upte lighway/Major Dis er drainage system all the campu	o nearest National strict Road) along m, Pathways and	"All approach co Highway/State H with storm wate landscaping for	oncrete roads (upte lighway/Major Dis er drainage syster all the campu	o nearest National strict Road) along m, Pathways and ses have to be 1 of Culvert, IRC

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				Class 70R/Class A/Class AA loading & other IRC Codes has to be followed as per approval of the Employer. Ministry of Road Transport Highways (MoRTH) Specification has to be followed for connection of Road with National Highway. In other instances respective authorities has to be contacted."	Class 70R/Class A/Class AA loading & other IRC Codes has to be followed as per approval of the Employer. Ministry of Road Transport Highways (MoRTH) Specification has to be followed for connection of Road with National Highway. In other instances respective authorities has to be contacted. Landscaping shall be required to be carried out over an area equivalent to approximately thrice the built up area of ground floor of structures to be constructed subject to availability of land."
9	136	Section-5.5 Scope & Specification of Civil Works	12.1 (2 nd Paragraph)	"• The employer reserves the right to conduct third party design validation by their 3rd party assessor and the successful bidder shall provide all data in soft and hard copy and carry out all modifications that may be suggested by the party so appointed. An authorized representative of the bidder will assist at the time of checking of structural design & drawings by 3rd party assessor for necessary clarification and for providing required data and statements to them."	"• The Employer shall provide the existing design based structural stability certificate of the existing structures which are available with the Employer, where vertical extension is required to be done to the bidders, if requested. The employer reserves the right to conduct third party design validation by their 3rd party assessor and the successful bidder shall provide all data in soft and hard copy and carry out all modifications that may be suggested by the party so appointed. An authorized representative of the bidder will assist at the time of checking of structural design & drawings by 3rd party assessor for necessary clarification and for providing required data and statements to them."
10	230	Section-5.6 Scope & Specification of Electrical Works	7.15A	After Clause 7.15, the following clause has been added	 "7.15A Specification of External High Mast Light a) 16 mtrs. height polygonal shape continuously tapered made from high tensile steel conforming to BSEN 10025 grade S355, having dimensions and thickness bottom A/F 410 mm, Top A/F 150mm plate thickness 4/3 mm, PCD 490 mm High Mast complete with base compartment with water proof door (consisting 3Ph power tool motor, mechanical torque limiter, double drum winch with 2 nos. 6 mm appropriate length SS wire rope, winch gear box, wire rope clamps & bobbin arrangement, removable handle for manual operation, plug & socket, PVC board, MCB box etc.), Mast header assemble fabricated from ERW steel

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
					 pipe with cable entry provision fitted with three-six pulley system which can accommodate wire ropes and electrical cables as per the requirements, to be provide single spike lightning final, aviation light fixing arrangement and all arrangement for fixing of luminaries. b) Foundation blots as per manufacturer specification and as direction by EIC for above pole along with nuts, washer, anchor plate and common template. c) LED type single dome aviation obstruction light (Bajaj/ approved make as direction by EIC. d) SITC highly efficient LED Flood light with lens made of pressure die cast aluminium housing, extruded aluminium heat sink & enclosed with toughened glass. IP66 200 Watt Make – Halonix (HLFLD-ML10-200-CWL)/Philips/Havells approved by / as direction by EIC. e) Foundation with M20 grade concrete considering safe soil bearing capacity at site as 10 T /sq mtr. at 2 mtr. Depth with all materials. Foundation design & drawing to be approved from EIC. f) Outdoor type stand mounted feeder piller box with timer made from 14 SWG MS sheet and 40mmx40mmx 5mm angle iron frame as required consisting with 1 no 32A FP MCB as incomer, 1 no. analog time switch, 1 no 25 amp TP contractor for lighting power supply and 2 nos. 9 amp TP contactor for power tool control and raise- lower push button, 60 Amp grade backlit/FRP connector 12 ways & neutral bar incl. internal connections and paintings.(size of piller box 900mmx450mmx 300mm with one side door opening) g) 3" dia. 1.5 Mtr. Long heavy gauge G.I. Pipe

Sl. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
					 (minipole) having 9" X 9" X 1/2" M.S. sole plate welded with drilled hole at bottom of the pole to be installed on roof of building with S.F. earthing bolts, nuts washers. h) Erection of Single GI Mini Tubular Pole of length as given below with/without sole plate & Cap etc. in CC foundation above roof surface after necessary cheaping roof (Proportion and dimension indicated below), having CC (6:3:1) muffing of size 450x450x600 mm above base block including 19mm plaster with 3 mm thick neat cemented finish and GI earth bolt after making drilled holes etc. on pole & carriage of pole upto 1.6 Km from Store to work-site including filling up the excavated earth pit with shifted soil and ramming properly incl. S&F of 200mmX150mmX100mm mm GI loop box in C.C foundation. i) Supply & fixing of single arm header assembly made with 100mm dia. GI pipe Jacket of 30cm long with 1.5 mtr. long 40mm dia. GI pipe bracket duly welded with top cap at an angle of 110 degree with the vertical incl. 12 mm dia. full threaded through nuts-bolts and 3 nos. supporting nut-bolts etc. including necessary painting as per direction of EIC. j) Connection, termination and commissioning of entire High Mast system with suitable sized cable, separate outdoor type electrical panel nearby and other accessories required for commissioning the entire system."
11	253	Section-5.6 Scope & Specification of Electrical Works	10	 Digital Amplifier: Input Voltage: 24 VDC Maximum DC Current: 10Amps Maximum Watts: 125/250Watt Operates on 220V, A.C supply. Battery backup with built in charging. Low battery visual warning with audible tone. DC Output indication. 	DELETED

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				 PA Ceiling Speaker: Flush mount 15cm dynamic cone speaker. Three field selectable power taps. ABS plastic grill with metal punched net. Easy to install with spring catch mount. Connectors with screw for hooking up the wires tightly. Protective dust cover at rear. The white color of the grill has been selected to be obtrusive in virtually all interiors. Power: 10W Toppings 100V line: 1.5W / 3W / 6W Sound Pressure Level : 92dB (1W,1M), Frequency : 60-15000Hz Material: ABS Plastic. Dimensions: ø160 mm, H 70 mm. PA Wall Speaker: Model Description Wall mounted with cone speaker for announcement and paging. Attractive, stylish ABS white plastic box. The specially designed slim speaker is obtrusive in all interiors. Equipped with the transformer to provide 100v line. Ideal for office cabin, work stations, classrooms, shops, malls etc. Optional Volume control. Music Power : 10W Impedance : 100V line Tapping's : 1.5, 3W, 6W Dynamic Cone Speaker : 1 X 12.5 CM Frequency : 60 - 15000Hz SPL@(1W/1M) : 90 dB Dimensions : (135 H X 190 L X 120D) mm 	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision			Changed Cla	use / Provision	I
				 Matching Transformer with multiple taps easily selectable by changing the rota the rear of the sealed assembly. This is indoor/outdoor application Input Power : 15W(RMS) 24W(Max Taps : 2.5W, 5W, 7.5W, 10W, 12.5W Impedance : 100V Line Frequency Response : 275 - 7000 H Type : ABS Plastic Size : 205 \$\u03c6\$ (271 L) SPL @1Khz : 106dB 	ary switch at ons. x) V, 15W				
12	260	Section-5.6 Scope & Specification of Electrical Works	13.1.1	Sl.BuildingMinimum quantity of liftNo.BuildingMinimum quantity of lift1Annex Building/ Academic41Annex Building/ Academic41Annex Building/ Academic41Annex Building/ Academic41Annex Building/ Academic41Annex Building/ Academic410Malda Medical passenger10Building (for Murshidabad16Murshidabad passenger16Murshidabad Medical College2PG Hospital2PG Mospital2PG Mospital2PG Mospital2PG Murshidabad Medical College2PG Murshidabad Medical College1(one) no. be passenger cum Murshidabad Medical College & 1 (one) & 1 (one)2PG Murshidabad Medical College & 1 (one) & 1 (one)2PG Murshidabad Medical College & 1 (one)3Medical College & 1 (one) & 1 (one)4Hospital Medical College & 1 (one)5Murshidabad & no. passenger6Mospital & no. passenger	Provision	2. PG Bui Meta & H	Building mex ilding/Acade c Building Murshidabad dical College Hospital c Hostel ilding for trshidabad dical College Hospital	Minimum quantity of lift shall be installed 4 (four) nos. bed cum passenger lift (20 passenger capacity)/As per requirement approved by EIC. 1 (one) no. be cum passenger lift (20 passenger capacity) & 1 (one) no. passenger lift (10 passenger capacity)/As per requirement approved by EIC.	Provision New Lifts shall be installed and commission ed. New Lifts shall be installed and commission ed.

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
13	264	Section-5.6	II.	Medicine & lift (08 Sagore Dutta passenger Hospital) capacity)/ As per requireme nt approved by EIC.	DELETED
	204	Section-3.6 Scope & Specification of Electrical Works	II. SPECIFIC ATION FOR ELECTRI CAL AND MECHANI CAL ENGINEE RING SERVICE S: 15. SPECIFIC ATION OF SOLAR SYSTEM	15. SPECIFICATION OF SOLAK SISTEM: Deliverable of 2×50 KWp Grid Connected Roof Top Solar PV Power Plant: A. Outline of the scheme of the project: • The array capacity of the proposed grid connected PV Power plants shall be 2x 50kWp for the entire campus. • The PV array shall be installed on the available space of the Roof of the Building. • The power plant shall be connected with grid with five numbers grid tie string inverters each of capacity 10 KVA, 3Ø 415 V 50Hz AC. • The inverters shall be installed in a suitable kiosk(s) with proper security protection close to the Array Terminal Box with arrangement of proper shed. • Outputs of the grid tie string inverter shall be terminated to an Inverter Combiner Panel to be located close to the inverters. • The output of the Inverter Combiner Panel shall be terminated and connected with supply mains through Grid interfacing Panel • An Export Import Energy Meter to be installed nearer to the Grid interfacing Panel before connected to the mains to measure the energy produce from the PV Power Plant A.8 The SPV power plant to be installed should be Robust, Economic, Efficient and Time tested. B. Solar PV Modules: The Cell of the Modules shall be poly crystalline. The capacity shall be consider as per declared capacity in the published technical brochures of the proposed PV Module Manufacturer. Minimum number of PV Cell 1 240 Wp/250 Wp 60 Nos. 2 290 Wp / 300 Wp 72 Nos. The PV modules must qualify the relevant IEC 61215 or IS 14286 and IEC 61730.The	DELETED

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				proposed PV Module must have the Test Certificate issued from accredited test laboratories of MNRE	
				Government of India under JNNSM Programme. The	
				test certificates issued from IEC accredited	
				laboratories shall also be acceptable. Proposed PV	
				Module must be manufactured in India. Each PV	
				module used in this solar power project must use an RF identification tag. The information must be	
				mentioned in the RFID used on each module as per	
				guideline of MNRE Government of India (This can be	
				inside or outside the laminate, but must be able to	
				withstand harsh environmental condition	
				Manufacturer of proposed PV modules must have the ISO 9001:2008 or ISO 14001 Certification for their	
				manufacturing unit for their said manufacturing item.	
				Desired specification of the PV Module shall include	
				but not limited to the following: Sl No Item	
				Description 1.0 Certification i) IEC 61215 or IS 14286	
				<i>ii) IEC 61730 1.1 Test certificate issuing authority.</i> <i>NABL/IEC Accredited Testing Laboratories or MNRE</i>	
				accredited test centers. 2.0 PV Cell 2.1 Type poly	
				crystalline 2.2 Size 156mmX156mm 3.0 PV Module	
				3.1 Rating at STC i)240 Wp/ 250Wp, 60 cells (without	
				any negative tolerance) ii)290 Wp / 300Wp, 72 cells	
				(without any negative tolerance) 3.2 Efficiency minimum14% 3.3 Fill factor Minimum 70% 3.4	
				Withstanding voltage 1000V DC 3.5 Glass 3.5.1	
				Thickness 3.2 mm (minimum) 3.5.2 Type High	
				transmission, low iron, tampered & textured glass	
				with anti reflective coating. 3.6 PV Module Junction	
				Box 3.6.1 Protection level IP 65 or above 3.7 Bypass	
				Diode 3.7.1 System Voltage (Vsys) 1000 V dc 3.7.2 Number 3 numbers 3.8 Module Frame 3.8.1 Type	
				Anodized aluminum frame C. PV Array Desired	
				specification of the PV Array shall include but not	
				limited to the following: Sl No Item Description 1.0	
				Nominal Capacity 1x50 KWp 2.0 PV Module	
				interconnection connector MC-4 / Tyco 3.0 PV Module interconnection cable and array cable PV 1-F	
				moaule interconnection cable and array cable PV 1-F	

Sl. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				standard /NEC standard "USE-2 or RHW-2" type (
				double insulated) 4.0 PV array String Voltage	
				Compatible with the MPPT Channel of the inverter 5.0	
				Number of Parallel String against each MPPT	
				Channel 02 Nos (Maximum) D. Array Structure i) The	
				solar PV system capacity minimum 100 KWp have to	
				install at shadow free multiple locations as per	
				availability of free roof top space of the buildings. ii)	
				PV Array structures shall be of Mild Steel with	
				combination of either of I, C, L sections MS flat as	
				per structure design requirement. The structure should	
				be capable of withstanding a wind load of 150 km/hr	
				after grouting & installation. iii) Weight of the	
				Metallic part of PV Array structure excluding nuts and	
				bolt must be minimum same as the Weight of the total	
				PV Module. iv) Structural shall be corrosion resistant	
				and electrolytically compatible with the materials used	
				in the module frame, its fasteners, nuts and bolts. v)	
				The array structure shall be made of hot dip	
				galvanized MS structure of minimum galvanizing	
				thickness 70 to 80 micron vi) Structures shall be	
				supplied complete with all members to be compatible for allowing easy installation. vii) The module	
				mounting structure shall have to be designed and	
				fabricated with optimum tilting angle considering the	
				site conditions. viii) The structure shall be designed	
				for simple mechanical and electrical installation. It	
				shall support SPV modules at a given orientation,	
				absorb and transfer the mechanical loads to the	
				ground. ix) All fasteners for supporting conduits, nut	
				& bolts shall be made with stainless steel, very good	
				quality stainless steel except foundation bolts and the	
				nuts and bolts to be used for connection of earthing	
				strip with module mounting structure which will be of	
				MS (GI Coated) x) Supporting structures including	
				module Mounting structure shall have to be	
				adequately protected against all climatic condition.	
				The array structure shall support SPV modules at a	
				given orientation and absorb and transfer the	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				mechanical loads to the columns properly. xi) The	
				structures shall be designed for simple mechanical	
				and electrical installation. There shall be no requirement of welding or complex machinery at the	
				installation site. Required civil work or support	
				platform is absolutely essential to install the	
				structures, detailed engineering drawings and	
				instructions for civil and other works shall got	
				approved from the competent authority before carried	
				out at the site. xii) The Specification of the MS	
				sections, flats must be as per IS 808 xiii) The supplier	
				shall specify installation details of the PV modules and	
				the support structures with appropriate diagrams and	
				drawings. E. PV Array Junction Box (AJB) Array	
				Junction Box (AJB) shall have to be used for	
				termination of string prior connecting array with each	
				inverter. There shall be two Arrays Junction Box	
				incase, the inverter is located elsewhere away from PV	
				Array. The minimum number of PV Array Junction Box shall be five (05) numbers. The desired	
				specification of the PV Array Junction Box and	
				accessories shall include but not limited to the	
				following: SI No Item Description Desired Data 1.0	
				Enclosure 1.1 Degree of Protection IP65 with UV	
				Protected 1.2 Material Polycarbonate. 1.3	
				Withstanding voltage 1000V DC 1.4 Withstanding	
				Temperature 100 0C 1.5 Accessories mounting	
				arrangement DIN Rail 1.6 Number of Strings entry As	
				may be required 1.7 Approved Make Hensel/	
				Spelsberg /ABB /Ensto or or equivalent make (as per	
				acceptability of authority) 2.0 Cable Entry and Exit	
				2.1 Position Bottom at cable entry and exit 2.2 Cable	
				Entry and Exit connector type MC 4 Connector (PV	
				Array String cable) 2.3 Cable gland Earthing cable entry 3.0 Surge Protecting Device (SPD) 3.1 Type DC	
				3.2 Approved Make OBO Betterman / Dehn / Citel	
				/ABB or equivalent make (as per acceptability of	
				authority) 3.3 Protection class Type $B+C$ 3.4 Number	
				of set As may be required as per string Design 3.5	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				System Voltage Matched with System Voltage 1000 V	
				DC 4.0 Fuse with fuse holder 4.1 Position Positive	
				and negative terminal for each series string 4.2 Type	
				Glass fuse, for PV Use only 4.3 Rating Current:	
				Minimum 1.25 times the rated short circuit current of	
				the string Voltage: Minimum 1000 V DC 5.0 Earthing	
				Provision Terminal blocks will have to be provided for	
				Earthing 6.0 Terminals, lugs and bus bar Tinned	
				copper F. Grid Connected Inverter The inverters shall	
				be of string inverter. The proposed $2x$ 50 KWp grid	
				connected solar PV power plant shall be connected	
				with grid. As such, the inverters shall be compatible to	
				operate with existing utility supply. The PV system	
				shall comprise of ten (10) numbers of grid tie inverters	
				each of nominal capacity 10 KVA. Desired	
				specification of each 10 KVA inverter shall include but	
				not limited to the following: Sl. No. Operating	
				Parameter Desired specification 1.0 Type Grid	
				connected String Inverter 2.0 Usage Specially used for	
				PV system 3.0 Standards 3.1 Efficiency Measurement	
				IEC 61683/ Equivalent BIS Std. 3.2 Environmental	
				testing IEC 60068-2 (1,2,14,30) / Equivalent BIS Std.	
				3.3 Interfacing with utility grid IEC 61727 3.4	
				Islanding Prevention Measurement IEC 62116 3.5 Type Test certificate issuing authority (for item no 3.1	
				, 3.2,3.3 and 3.4) NABL/ IEC Accredited Testing	
				Laboratories or MNRE approved test centers. 4.0	
				Input (DC) 4.1 PV array connectivity capacity 12	
				<i>KWp (minimum) 4.2 MPPT Voltage range Compatible</i>	
				with the array voltage 4.3 Number of MPPT Channel	
				2 nos (Minimum) 5.0 Output (AC) 5.1 Nominal AC	
				Power output 10 KVA 5.2 Number of Grid Ph 3Ø 5.3	
				Adjustable AC voltage range Programmable as per	
				grid condition 360V455V 5.4 Frequency range 47-53	
				Hz 5.5 AC wave form Sine wave 5.6 THD Less than	
				3% 5.7 Switching High frequency transformer /	
				transformer less 6.0 General Electrical data 6.1	
				Efficiency (Maximum) 95 % 6.2 Sleep mode	
				consumption Less than 5 W 7.0 Protection 7.1 DC	
	l			consumption Less than 5 w 7.0 Frolection 7.1 DC	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				Side 1. Reverse-polarity protection 2. Reverse current	
				to PV array protection, over voltage, Under voltage	
				protection 3. Over current 7.2 AC side 1. DC inject	
				protection to grid less than1% 2. Over voltage and	
				Under voltage 3. Over current 4. Over and under grid	
				frequency protection, 5. Anti Islanding protection 7.3	
				Isolation Switch PV array Isolation switch (DC) 7.4	
				Ground fault detection device (RCD) which can detect	
				changes in ground current. Rating shall be as suitable	
				for inverter To be provided for transformer less	
				inverter. 8.0 Display 8.1 Display type LCD Display	
				8.2 Display parameter 8.2.1 DC Voltage Current	
				Power 8.2.2 On grid connected mode Line status Grid	
				voltage Grid frequency Export Power Cumulative	
				Export Energy 9.0 Interface (Communication	
				protocol) Suitable port must be provided in the inverter for i) On site upgrade of Software, ii) On site	
				dumping data from the memory, iii) Web based remote	
				monitoring system 10.0 Web monitoring Matched with	
				the monitoring and data logging system 11.0	
				Mechanical Data 11.1 Protection Class IP 65 or	
				higher 11.2 Operating ambient temperature 0 0C to	
				600C 11.3 Cooling Natural / forced cooling G. Web	
				enable on line data logger and Remote Monitoring	
				Unit: Web enable data logging system may be an	
				integrated part of the inverter or a separate unit. The	
				data logging system includes MPPT wise PV array	
				monitoring system also. The data Logger should have	
				the provision of recording the data of solar insulation,	
				PV cell temperature and ambient temperature and	
				associated electrical parameters at different stages to	
				study performance of system as well as to study status	
				of the system at a particular instant. The data logger	
				should have required transducer to monitor and	
				record the required system data. The data logger	
				should be provided with an insulation sensor and a	
				module temperature sensor, ambient temperature	
				sensor matched with the system. The data logger shall	
				have reliable battery backup and data storage	

Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
			capacity (minimum two days data) to record all sorts	
			of data simultaneously round the clock. Web based	
			Remote Monitoring system must be compatible with	
			data logger. The system shall be provided with GSM	
			Modem with required SIM card. The modem must be	
			1	
			-	
			-	
			•	
			0	
			-	
	-	- Nection	Section	No. Section No. Current Clause / Provision Image: No. Capacity (minimum two days data) to record all sorts of data simultaneously round the clock. Web based Remote Monitoring system must be compatible with data logger. The system shall be provided with GSM

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				after opening of front doors. The front door must have	
				locking arrangement. Desired specification of Grid	
				Sink Panel shall include but not limited to the	
				following: Sl. No. Parameter Desired Specification 1	
				In coming MCB (Inverters side) 1.1 Approved make	
				ABB / L & T / Schneider /	
				Siemens/Havell'sorequivalent make (as per	
				acceptability of authority) 1.2 Number 06 (one)	
				number. 01(one) number against each inverter and	
				one number spare. 1.3 Type 4 pole 1.4 Rating 415V,	
				32 Amps, 10 kA 2 Outgoing MCCB (Grid Side) 2.1	
				Approved Make ABB / L&T / Siemens/ Schneider or	
				equivalent (as per acceptability of authority) 2.2 Type	
				4 pole 2.3 Rating 125A 415VAC 50kA 3 Surge	
				protection device 3.1 Position Outgoing side (Grid	
				side) 3.2 Approved Make OBO Betterman / Dehn /	
				Citel /ABB or equivalent make(as per acceptability of	
				authority) 3.3 Usage as declare by Manufacturer For AC use only 3.4 Protection class Type B+C 3.5	
				Number of set 01 Set 3.6 Rating 600 V 100 kA	
				(minimum) 4 AC load break switch 4.1 Make ABB /	
				<i>L&T / Siemens/ Schnider /Havell's or equivalent make</i>	
				(as per acceptability of authority) 4.2 Rating 150A 415	
				V TPN 4.3 Operating facility Handle with Padlock. 5	
				Indicator Incoming side and outgoing side (R,Y,B) 6	
				Metering Arrangement 6.1 Instantaneous Measuring	
				parameter i. Voltage, ii. currentiii. Frequency 6.2 CT/	
				PT Make KAPPA/ SERVO/AE/ KALPA or equivalent	
				make (as per acceptability of authority). 6.3 Type of	
				meter Electronics 6.4 Display type of meter LED/LCD	
				6.5 Display of the meter From outside without opening	
				of front cover 6.6 Meter Make L&T / Siemens/	
				Schneider/ Secure or equivalent (as per acceptability	
				of authority) 7 Bus Bar 7.1 Material Copper 7.2 Type	
				TPN 7.3 Rating 200 A 7.4 Position Incoming and Out	
				Going Bus 8 Earthing Provision Terminal Blocks will	
				have to be provided for Earthing 9 Mechanical 9.1	
				Type Metallic, double door, Outdoor Type 9.2	
				Protection level IP 54 (minimum) 9.3 Housing Floor	

No. N	age No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
	40 .		NO.	Mounted/ Wall Mounted 9.4 Enclosed Double Door Metal Enclosure dust and vermin proof 9.5 Cable Entry Top/Bottom (as per approval) 9.6 Glands Position At cable entry and exit 9.7 Cooling Natural/ forced I. Kiosk (for installation of Array Junction Box, Inverter, Grid Sync Panel): (i) All the Array Junction Boxes, Inverters and Grid Sync Panel shall be installed at the same place and at the rare side of the PV Array in a suitable location in a Kiosk. (ii) The kiosk of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosk must have security arrangement against theft, manhandling etc. Above the kiosk there should have a suitable shade. (iii) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (iv) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (v) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (vi) The cable laid in the kiosk through cable tray with front cover. (vii)The Kiosk structure must have sufficient strength to bare the load of the equipments. J. Grid interfacing LT Panel Output of each of the two Inverter combiner panel shall be terminated to a Grid Interfacing LT Panel. The Inverter Combiner Panel shall be outdoor type Poly Carbonate of protection level IP 65. All the equipments and meter display can only be accessed after opening of front doors. The front door must have locking arrangement. Desired specification of each Grid interfacing LT Panel shall include but not limited to the following: Sl. No. Parameter Desired Specification 1.0 MCCB (Grid Side) 1.1 Number 02 (two) numbers. 01(one) number to be used + 01 Number spare 1.2 Approved Make ABB / L&T / Siemens/ Schneider or equivalent (as per acceptability	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				of authority) 1.3 Type 4 pole with handle 1.4 Rating 125A 415VAC 50 kA 2.0 Surge protection device 2.1	
				Position Outgoing side (Grid side) 2.2 Approved	
				Make OBO Betterman / Dehn / Citel /ABB or	
				equivalent make (as per acceptability of authority) 2.3	
				Usage as declare by Manufacturer For AC use only	
				2.4 Protection class Type $B+C$ 2.5 Number of set 01	
				Set 2.6 Rating 600 V 100 kA (minimum) 3.0 Metering	
				Arrangement 3.1 Instantaneous Measuring parameter i. Voltage, ii. current iii. frequency iv. Power 3.2 CT/	
				PT Make KAPPA/ SERVO/AE/ KALPA or equivalent	
				make (as per acceptability of authority). 3.3 Type of	
				meter Electronics 3.4 Display type of meter LED/LCD	
				3.5 Display of the meter From outside without opening	
				of front cover 3.6 Meter Make L&T / Siemens/	
				Schneider/ Secure or equivalent (as per acceptability	
				of authority) 4.0 Earthing Provision Terminal Blocks	
				will have to be provided for Earthing 5.0 Enclosure 5.1 Degree of Protection IP65 with UV Protected 5.2	
				Material Polycarbonate. 5.3 Withstanding voltage	
				1000V DC 5.4 Withstanding Temperature 100 0C 5.5	
				Number of Strings entry As may be required 5.6	
				Approved Make Hensel/ Spelsberg /ABB /Ensto oror	
				equivalent make (as per acceptability of authority) 5.7	
				Cable Entry Bottom K. Export Import Energy Meter:	
				One number 3 \emptyset 4 wire 415V AC 3X(20A-100A)	
				whole current Export Import Energy Meter of $L\&T / C$	
				Genus or Equivalent per acceptability of authority. The	
				Meter to be supplied must be tested from any of the NABL/ BIS Accredited Testing-Calibration	
				Laboratories. The export Import Energy meter shall	
				be installed at the separate housing within an	
				enclosure. The Export Import Energy meter shall be	
				installed at a suitable location before Point of	
				Common Coupling (PCC) with grid side. L. Cables &	
				Wirings : The Specification of wiring material of PV	
				Power plant shall include but not limited to the	
				following: Sl. No. Item Description A DC Cable 1.1	
				Conductor Tinned annealed stranded flexible copper	

according to IEC 60228 class 5 1.2 Standard PV-IF / 2 PfG 1169/08.2007 / VDE Standard E PV 01.2008-02 /Equivalent 1.3 Make LAPPTop Solar/Nexans/ Schneider or equivalent (as per acceptability of authority) B AC Cable 2.1 Rated Voltage 1.1KV 2.2 Construction 2.2.1 Type Armored or unarmored as per requirement 2.2.2 Conductor Stranded flexible copper 2.2.3 Insulation PVC SI No Item Description 2.2.4 Standard IS : 1554 -1 2.3 Make RR Cable/ Polycab1.APP/ Ilavell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC to 50 0C 3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Intwerters Inverter Combuer Ponel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be pai in a Riosk (ii) The panels must be installed in suitable kiokss protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoiled. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good ari circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoiled. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good ari circulation. The Kiosk must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoiled between Array structure and the equipment and equipment structure (iv) The minimum clearance of the lower edge of the equipment fixed on the array structure then suitable insultation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipment fixed on the a	SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
/Equivalent 1.3 Make LAPPTop Solar/Netams/ Schneider or equivalent (as per acceptability of authority) B AC Cable 2.1 Rated Voltage 1.18V 2.2 Construction 2.2.1 Type Armored or unarrowed as per requirment 2.2.2 Conductor Stranded flexible copper 2.2.3 Issuadation PVC SI No Item Description 2.2.4 Standard IS : 1554 1.2.3 Make RR Cable/ Polycab/LAPP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tess, bends et (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0.0C to 500 C3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast / Slapreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiodsx protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against the; standation must be provided between Array structure and the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipapment fixed on th					according to IEC 60228 class 5 1.2 Standard PV-1F /	
Schmeider or equivalent (as per acceptability of authority) B AC Cable 2.1 Rued Voltage 1.1kV 2.2 Construction 2.2.1 Type Armored or unarmored as per requirement 2.2.2 Conductors Stranded flexible copper 2.2.3 Insulation PVC SI No Hem Description 2.2.4 Standard IS : 1554 -1 2.3 Make RR Cable/ Polycab/LAPP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC to 500 C 3.2 Type UV stabilized , temperatures, Shock proof chenical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make ATATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in stuibable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks must have suitable abed so that rain water and direct sun exposure can be avoided. (iii) The kiosks must have suitable beds so that rain water and direct sun exposure can be avoided. (iv) The kiosks must have suitable beds so that rain water and direct sun exposure can be avoided. (vi) The kiosks must have suitable beds so that rain water and direct sun exposure can be avoided. (vi) The kiosks must have suitable beds so that rain water and direct sun exposure (can be avoided on the array structure of the equipment fixed on the dary structure then suitable installation must be provided between Array structure and the equipment for the dowed on the array structure and the equipment for the dowed on the array structure then suitable installation must be provided between Array structure and the equipment fore do no the array structure then suitable fe					2 PfG 1169/08.2007 / VDE Standard E PV 01:2008-02	
authority) B AC Cable 2.1 Raied Voltage 1.1kV 2.2 Construction 2.2.1 Type Armored or unarmored as per requirement 2.2.2 Conductor Stranded Jexible copper 2.2.3 Insulation PVC SI No Item Description 2.2.4 Standard IS : 1554 -1 2.3 Make RR Cable/ Polycab/LAPP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & Jexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0.0 Ct o 50 C 3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Ktosks, Grid Inter facing panel also to be put in a Kitosk (ii) The panels must be installed in suitable kitosk iii) The panels must be installed in suitable kitosk with train water and direct sun exposure can be avoided. (iii) The kitosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kitosks must have security arrangement against theft, manhandling etc. (iv) The kitosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (iii) The kitosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kitosks must have security arrangement against theft, manhandling etc. (iv) The kitosks must have suitable sheds so that rain water and direct sun exposure can be equipment with good air circulation must be provided between Array structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (iv) The minimum clearance of the lower edge of the equipment from the developed ground level should be Im. (vii) The kitosk of must be of a suitable design covered with a cage with door and locking arrangement protection and to prevent mishandling. (viii) The cable laid in the					/Equivalent 1.3 Make LAPP/Top Solar/Nexans/	
Construction 2.2.1 Type Armored or nummored as per requirement 2.2.2 Conductor Stranded flexible copper 2.2.3 Insulation PVC SI No Item Description 2.2.4 Standard IS : 1554 -1 2.3 Make RR Cable/ Polycab/LAPP Havel'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC to 50 OC 3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Penel shall be instable d at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk Grid Inter facing panel also to be put in a Kiosk protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosk must have security arrangement agains theft, monhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks must have suitable design, covered with a door and locking arrangement with good air circulation. The Kiosk must have security arrangement against theft, monhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable instalton must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipment from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (vii) The cable laid in the						
requirement 2.2.2 Conductor Strandord [Exible copper 2.2.3 Insulation PVC SI No Item Description 2.2.4 Standard IS : 1554 -1 2.3 Make RR Cable/ Polycab/LAPP/ Polycab/LAPP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC 105 0C 5.2 Type UV stabilized, temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable blacks on that rain water and direct sun exposure can be avoided. (v) The equipment structure on the equipment fixed on the						
2.2.3 Insulation PVC SI No Item Description 2.2.4 Standard IS : 1554 -1 2.3 Make RR Cable/ PolycabLAPP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC to 50 OC 3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oripland /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosk must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable is beds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment ard direct sun exposure can be avoided (v) The equipment / structure of the equipment and developed ground level should be Im, (vii) The kiosk of must be of a suitable beinstaling must be provided between Array structure and the equipment and equipment structure, (vi) The minimum clearance of the lower edge of the equipment for the developed pround level should be Im, (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement provide level laid in the						
Standard IS : 1554 -1 2.3 Make RR Cable/ Polycab/APP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 0C to 50 0C 3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D Gl Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (iii) the kiosks posure can be avoided. (iii) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable installation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipment fixed on the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling, (viii) The cable laid in the					-	
Polycab/LAPP/ Havell'sor equivalent (as per acceptability of authority) C PVC Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 0C to 50 0C 3.2 Type UV stabilized , temperatures. Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimun clearance of the lower edge of the equipment fixed on the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement with a cage with door and locking arrangement with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
acceptability of authority) C PVČ Conduit tees, bends etc (Hard & flexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC to 50 OC 3.2 Type UV stabilized, temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D Gl Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door allocking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The kiosk of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a coage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
etc (Hard & ftexible) 3.0 Standard ASTM D 1785 u PVC 3.1 Ambient Temperature 0 OC to 50 OS 2.7 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhanling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (iv) The kiosks must have suitable sheds on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable heads of that cage with door and locking arrangement against the kiosk of must be of a suitable locial in the						
PVC 3.1 Ambient Temperature 0 0C to 50 0C 3.2 Type UV stabilized , temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure them suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The kinosk of must be of a suitable eign covered with a cage with door and locking arrangement array structure time sitable insulation must e of a design covered with a cage with door and						
UV stabilized, temperatures, Shock proof chemical resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks, Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipment fixed on the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a doe and edge for the equipment and more the lower edge of the equipment and developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishanding. (viii) The cable laid in the						
resistant 3.3 Make Oriplast /Supreme D GI Pipe 4.0 Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Klosks. Grid Inter facing panel also to be put in a Klosks Grid Inter facing panel also to be put in a Klosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The klosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Klosks must have security arrangement against theft, manhandling etc. (iv) The klosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (iii) The klosks of the equipment fixed on the array structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The klosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					1 1	
Make TATA (i) All the Array Junction Boxes, Inverters Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (v) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement and to prevent mishandling. (viii) The cable laid in the						
Inverter Combiner Panel shall be installed at the rare side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
side of the PV Array in suitable locations in Kiosks. Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable for a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
Grid Inter facing panel also to be put in a Kiosk (ii) The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
The panels must be installed in suitable kiosks protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					· ·	
protected from theft and mishandling with sheds so that rain water and direct sun exposure can be avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
avoided. (iii) The kiosks of must be of a suitable design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					•	
design, covered with a door and locking arrangement with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
with good air circulation. The Kiosks must have security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					avoided. (iii) The kiosks of must be of a suitable	
security arrangement against theft, manhandling etc. (iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					design, covered with a door and locking arrangement	
(iv) The kiosks must have suitable sheds so that rain water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					5	
water and direct sun exposure can be avoided. (v) The equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
equipment / structure of the equipment fixed on the array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
array structure then suitable insulation must be provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					-	
provided between Array structure and the equipment and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
and equipment structure. (vi) The minimum clearance of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
of the lower edge of the equipments from the developed ground level should be 1m. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
developed ground level should be Im. (vii) The kiosk of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the					1 1	
of must be of a suitable design covered with a cage with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
with door and locking arrangement for protection and to prevent mishandling. (viii) The cable laid in the						
to prevent mishandling. (viii) The cable laid in the						
Kiosk structure must have sufficient strength to bare						

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				the load of the equipments. M. System, Equipment, Array structure Earthing: i. Equipment grounding (Earthing) shall connect all non-current carrying metal receptacles, electrical boxes, appliance frames, chassis and PV panel mounting structures in one long run. The grounding wire should not be switched, fused or interrupted. ii. Array Structure must be earthed with GI Strip iii. The complete earthing system shall be electrically connected to provide return to earth from all equipment independent of mechanical connection. iv. The equipment grounding wire shall be connected to one grounding electrode per PV power plant. v. Test point shall be provided for each earth pit. vi. An earth bus and a test point shall be provided inside control room. vii. Earthing system design should be as per the standard practices. viii. The Earthing pit must be of Chemical gel type with Chem- Rod as grounding rod. ix. The Code of Practice Earthing shall be IS 3043:1987 x. Necessary provision shall be made for bolted isolating joints of each earthing pit for periodic checking of earth resistance. xi. Minimum six (06) numbers of earth pit. Earthing Pit Cover Needs to be provided xii. Earth Grid must be made by inter connection of earth pit through GI Strip. The size of the GI earth strip must be minimum 25X3 mm. The thickness of the galvanization should be as per the relevant standard. N. Lightning Protection (i) The Code of Practice of lightning protection system shall be IS 2309: 1987 (ii) Suitable number of Lightning Protection Unit comprises of GI Air Terminal with G.I. pipe of suitable height for mounting the terminal & adaptor must be provided to cover the complete PV Array yard. (iii) Minimum four (04) numbers lightning arrestor shall be separate from the system/equipment earthing. (v) Chemical gel type of earthing must be used for earth pit. (vi) The two pits shall be interconnected at a suitable location outside the of the building by a earth bus with test	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				jumper. (vii) Lightning arrestors shall be interconnected connected and earthed to the lightning protection system through the GI strip (viii) The size of the GI earth strip used for Lightning Protection system must be minimum 50X5 mm. (ix) Minimum five (05) numbers of earth pit for lightning arrestor. (x) The number of air terminal must be such so that it can cover the total PV array. O. Signage: Safety Signage: Safety Signage must be provided mentioning the level and type of voltage and symbols as per IE Rule at different position as may be required. P. Provision for Module Cleaning Module Cleaning: Necessary arrangement and equipment is to be provided to facilitate easy cleaning of the PV Modules Q. Fire Buckets and Fire Bucket Holding stand Fire Bucket of minimum quantity eight (08) numbers and Fire Bucket of minimum quantity two (02) shall be provided at Array field. Each fire Bucket holding stand (Triangular type) shall have the arrangement to hold four (04) numbers of fire buckets. The Fire Bucket stand must be as per IS 2546. The stand shall be installed at the rare side of the PV Array. The minimum technical specification is a follows: Bis Specification IS 2546 Fire Bucket Capacity 10 Litres Fire Bucket Body Material Galvanized Mild Steel Sheet Body Thickness 1 mm R. Spares ,Tools and Measuring Instruments: The minimum number and different type of spares, tools and measuring instruments must be supplied under this project within the contract value. Also any special tools, spares, measuring instruments if required as may be shall be provided by the contractor. Special Terms and Condition A. Field Proven Inverter The propose string inverter must be field proven in Indian atmosphere. The string inverter of the proposed manufacturer must be used in any project of minimum capacity 2X50 KWP. Also there must be a good maintenance setup of the proposed inverter manufacturer with having sufficient numbers of qualified service engineers	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				(Degree/Diploma engineers) and well equipped set up with instruments, tools and tackles at anywhere in	
				West Bengal. The maintenance setup of the proposed	
				inverter manufacturer may be inspected by authority,	
				if required. B. Equipment and Material Equipment and	
				material shall comply with description, rating, type	
				and size as detailed in this specification. Equipment	
				and materials furnished shall be complete and	
				operative in all respect. All accessories, which are	
				necessary for safe and satisfactory installation and	
				operation of the equipment, shall be furnished. All parts shall be made accurately to standard gauges so	
				as to facilitate replacement and repair. All	
				corresponding parts of similar equipment shall be	
				interchangeable. Contractor shall carefully check the	
				available space and the environmental conditions for	
				installation of all equipments available at site and	
				shall design the system accordingly. C. Mode of	
				Execution The PV power plant shall be procured as a	
				complete package. The entire work shall have to be executed on turnkey basis. Any minor item(s) not	
				included in the schedule or specification but required	
				for completion of the work shall have to be carried	
				out/supplied without any extra cost. While submitting	
				the offer the bidder shall consider cost of those items	
				and may indicate separately as additional deliverable	
				items. D. Materials and Workmanship Qualified,	
				experienced people should be deployed to install the	
				PV Power Plant. All materials shall be of the best	
				quality and workmanship capable of satisfactory	
				operation under the operating and prevailing climatic conditions of respective. Unless otherwise specified,	
				they shall conform in all respect to the latest edition of	
				the relevant code and standards. The project must be	
				supervised by a qualified Structural Engineer/	
				Engineering firm and Electrical /Electronics Engineer	
				so that the work shall be as per drawing and related	
				IS/IEC Code. The work shall be performed confirming	
				safety precaution of all level of worker execute the	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				project. The name and the qualification of the project engineers must be submitted to authority after	
				placement of order. The qualification of the	
				supervising engineers must be minimum degree or	
				diploma in respective stream. E. Testing and	
				Inspection Material Inspection will be carried out	
				after submission of all test reports /certificates and	
				after completion of the manufacturing work, against formal intimation from the contractor. The contractor	
				shall, give notice of any material being ready for	
				testing and the authority, if desired, shall attend at the	
				contractor's premises and may proceed with the	
				routine tests. The material shall have to be dispatched	
				at site after inspection and clearance from the	
				purchaser. The inspection setup and instruments must	
				be provided by the contractor within the contract value. F. Commissioning After the erection and testing	
				of the equipment/works as per above, commissioning	
				of the plant and works shall be carried out and here	
				the term "Commissioning" shall mean the activities of	
				functional testing of the complete system after erection	
				and testing, including tuning or adjustment of the	
				equipment for optimum performance and	
				demonstrating to the Purchaser that the equipment performance meets the requirements of the	
				specifications. G. Insurance: Execution Insurance: It	
				is desired that the contractor shall arrange for	
				insurance coverage for the equipment, accessories,	
				materials etc. to be delivered at site up to handing	
				over of the complete installation. As such the bidder	
				shall include the cost of such insurance in their price	
				bid. Insurance after commissioning of PV Power	
				Plant: Insurance against Fire, natural calamitiesshall be arranged by the Contractor for entireperiod of	
				contract (i.e. three years from the date of handover of	
				the power plant)." H. Comprehensive Warrantee and	
				Maintenance The Contractor must ensure that the	
				goods supplied under the contract are new, unused	
				and of most recent or current models and incorporate	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				all recent improvements in design and materials unless provided otherwise in the Contract. The	
				warrantee period of the complete PV Systems will be	
				36 (Thirty six) calendar months from the date of	
				handover. The Contractor shall remain liable to	
				replace any defective parts that may develop in the	
				plant of his own manufacture or that of his sub-	
				contractors under the conditions provided for by the	
				contract under proper use, and arising solely from	
				faulty design, materials or workmanship, provided	
				always that such defective parts as are not, repairable at site and are not essential in the meantime to the	
				maintenance in commercial use of the plant are	
				promptly returned to the contractor's works at the	
				expense of the contractor unless otherwise arranged.	
				The maintenance includes Routine, Preventive,	
				Breakdown & Capital Maintenance the details are as	
				follows but not limited: Routine, Preventive,	
				Breakdown & Capital Maintenance: Routine and	
				preventive maintenance: Routine and preventive	
				maintenance shall include cleaning of PV Module on regular basis, checks and maintenance activities such	
				as tightening of all electrical connections, daily,	
				weekly, fortnightly, monthly, quarterly, half yearly,	
				and yearly basis which are required to be carried out	
				on all the components of the power plant to minimize	
				breakdowns and to ensure smooth and trouble free	
				running of the power plant. The supplier shall be	
				responsible to carry out routine and preventive	
				maintenance and replacement of each and every	
				component / equipment of the power plant and he shall provide all labour, material, consumables etc. for	
				routine and preventive maintenance at his own cost.	
				Breakdown maintenance: Breakdown maintenance	
				shall mean the maintenance activity including repairs	
				and replacement of any component or equipment of	
				the power plant which is not covered by routine and	
				preventive maintenance and which is required to be	
				carried out as a result of sudden failure/breakdown of	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				that particular component or equipment while the plant is running. The supplier shall be responsible to	
				carry out breakdown maintenance of each and every	
				component of the power plant and he shall provide the	
				required manpower, materials, consumables,	
				components or equipment etc. for breakdown	
				maintenance at his own cost irrespective of the	
				reasons of the breakdown/failure Capital	
				maintenance: Capital Maintenance shall mean the	
				major overhaul of any component or equipment of the power plant which is not covered by routine,	
				preventive and breakdown maintenance which may	
				become necessary on account of excessive wear &	
				tear, aging, which needs repair/replacement. The	
				capital maintenance of power plant and all civil	
				structures shall normally be planned to be carried out	
				on an annual basis. For this purpose a joint inspection	
				by the supplier and purchaser shall be carried out of	
				all the major components of the power plant, about	
				two months in advance of the annual maintenance period, in order to ascertain as to which components	
				of the power plant require capital maintenance. In this	
				regard the decision of the purchaser will be final and	
				binding. However, if the condition of any plant and	
				component warrants its capital maintenance at any	
				other time, a joint inspection of the purchaser and	
				supplier shall be carried out immediately on	
				occurrence of such situation and capital maintenance	
				shall be carried out by arranging the shutdown of the plant/part of the plant, if required, in consultation with	
				concerned authorities. The decision of the purchaser	
				shall be final and binding. Capital maintenance also	
				includes replacement of defective lights fans under the	
				project supplied by the contractor. The capital	
				maintenance includes painting, of mechanical	
				structure, civil structure. The contractor shall under	
				take necessary maintenance/troubleshooting work of	
				the Solar PV Power Systems. Down time shall not be	
				more than 72 working hours from time of occurrence.	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				Adequate measures should be taken for prevention of wear and tear of the machines. Solar PV Power System is to be designed to operate with a minimum of maintenance. The scope of Support Service provides preventive maintenance as & when necessary within the contract period and break down maintenance in the event of malfunctions, which prevent the operation of the power system or part of it within the stipulated time period & free replacement of spares required for maintenance. Party will provide the A list of Spare parts & measuring instruments are The contractor will submit warrantee certificates of the work & spare parts and materials at the time of submission of	
				completion report. If any defect is found within the warrantee period, contractor will be liable to repair or replace the same at his own cost and risk, within three (72 hours) days from the date of complaint lodged by the authority or by the user himself. I. End Users Training The Contractor shall arrange for training at site for the end users. The duration of training shall be minimum five days. The contractor shall provide training materials at least seven days before commencement of training programme. The training shall be the part of contract and no extra cost shall be provided for organizing the training programme. J. Handing Over The work shall be taken	
				over by authority upon successful completion of all tasks to be performed at site(s) on equipment supplied, installed, erected, commissioned AND RUN SUCCESSFULLY FOR CONSECUTIVE 60 DAYS AT A STRETCH by the contractor in accordance with provision of this order. During handing over complete project work, the contractor shall submit the followings for considering final payment. i. All As- Built Drawings & Design ii. ii. Detailed Engineering Document with detailed specification, schematic drawing, and test results, manuals for all deliverable major items, Operation, Maintenance & Safety Instruction Manual and other information about the	

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision Changed Clause / P	Provision
				project iii. Certificate issued by the structural & civil engineer/firm having engineer with minimum LBS/ESE/EBA License for structural design of PV Array. iv. Bill of material v. Inventory of spares at projects site vi. Completion certificate as per prescribed format provided by authority."	
14	361	Section 5.8 Payment Schedule	44	Sl.Activity/ Milestone% of Project% of ProjectSl.Activity/ Milestone% ProjectMilestoneProject Cost for Annex BuildingProject Cost for Hostel BlockSl.Activity/ Milestone% Project Cost Annex Building	t for Cost for ex Hostel
15	375	Section – 6 General Conditions of Contract ("GCC")	4.4	"Mobilisation Advance not exceeding 10% of the Contract Price may be given by the Employer at its sole discretion, if requested by the Contractor in writing within 30 (thirty) days of the issue of Notification of Award. The Employer may decide to pay the Mobilisation Advance to the Contractor, in the following 2 tranches, upon completion of the following events :- (a) First tranche of the Mobilisation Advance (a) First tranche of the Mobilisation Advance equivalent to 5% of the Contract Price shall be paid by the Employer, upon completion of the following (i) Construction of labour camp, Contractor's site (ii) Construction of the Contract Price shall be paid by the Employer, upon completion of the following (ii) Construction of the Employers' temporary site office and making arrangements for water supply (iii) Obtaining a Mobilisation Advance Bank Guarantee from a scheduled bank as per form given in Guarantee from a scheduled bank as per form given in Section - 7 (Contract Forms) aggregating to 5% of the Contract Price, being equivalent to the first tranche of the Mobilization Advance, in favour of the Employer and submission of such Bank Guarantee to the I0% of the value of all the Statement I0% of the value of all the Statemen	if requested by the ting within 30 (thirty) Award. The Employer ce to the Contractor, vents :- Contractor's site office er supply ' temporary site office ance Bank Guarantee n given in Section - 7 nt equivalent to the of the Employer and the to the Employer. The shall bear simple Repayment of the ence from payment of the Contractor after n Advance and shall interim Payment (@

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				(b) Second tranche of 5% of Mobilisation Advance will be released by the Employer to the Contractor, upon completion of payment by the Employer, of 15% of the total Contract Price and upon the Contractor obtaining a Mobilisation Advance Bank Guarantee from a scheduled bank as per the form given in Section – 7 (Contract Forms) aggregating to 5% of the Contract Price, being equivalent to the second tranche of the Mobilization Advance, in favour of the Employer and submission of such Bank Guarantee to the Employer. The Mobilisation Advance above shall bear simple interest @ 10% per annum. Repayment of the Mobilisation Advance shall commence from payment of the Statement first raised by the Contractor after disbursement of first tranche of the Mobilisation Advance and shall be entered as a deduction from Interim Payment (@ 10% of the value of all the Statements paid so far + simple interest @ 10% of the total Mobilisation Advance amount). For subsequent Statements, Mobilisation Advance shall be deducted from the Interim Payment @ 10% of the value of such	Recovery of advance at any intermediate stage shall be effected, if necessary, by encashment of part of the Mobilisation Advance Bank Guarantee if the appropriate pro-rata amount of advance is not available from the Works done by the Contractor. If the circumstances are considered reasonable by the Employer, the period mentioned for request by the Contractor in writing for grant of Mobilisation Advance may be extended in the discretion of the Employer. The said Mobilisation Advance Bank Guarantee for advances shall initially be made for the full amount and valid for the Contract period and be kept renewed from time to time to cover the balance amount and likely

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				Employer. The said Bank Guarantee for Mobilisation Advance shall initially be made for the full amount and valid for the Contract period and be kept renewed from time to time to cover the balance amount and likely period of complete recovery."	
16	385	Section – 6 General Conditions of Contract ("GCC")	4.24	"The Contractor shall take all reasonable steps to protect the environment (both on and off the Site) and to limit damage and nuisance to people and property resulting from pollution, noise and other results of its operations. The Contractor shall maintain ecological balance by preventing deforestation, water pollution and defacing of natural landscape. The Contractor shall so conduct its construction operations as to prevent any avoidable destruction, scarring or defacing of natural surrounding in the vicinity of work. In respect of ecological balance, the Contractor shall observe the following instructions for which no extra payments will be made: (a) Where destruction, scarring, damage or defacing may occur as a result of operations relating to Permanent or Temporary Works, the same shall be repaired, replanted or otherwise corrected at Contractor's expense. All work areas shall be smoothened and graded in a manner to conform to natural appearance of the landscape as directed by the Employer's Representative. (b) All trees and shrubbery, which are not specifically required to be cleared or removed for construction purposes, shall be preserved and shall be protected from any damage that may be caused by Contractor's construction operations and equipment or by their employees/ workers. The removal of trees or shrubs will be permitted only after prior approval of the Employer's Representative. Special care shall be exercised where trees or shrubs are exposed to injuries by construction equipment, blasting, excavating, dumping, chemical damage or other operation and the Contractor shall adequately protect	"The Contractor shall take all reasonable steps to protect the environment (both on and off the Site) and to limit damage and nuisance to people and property resulting from pollution, noise and other results of its operations. The Contractor shall maintain ecological balance by preventing deforestation, water pollution and defacing of natural landscape. The Contractor shall so conduct its construction operations as to prevent any avoidable destruction, scarring or defacing of natural surrounding in the vicinity of work. In respect of ecological balance, the Contractor shall observe the following instructions for which no extra payments will be made: (a) Where destruction, scarring, damage or defacing may occur as a result of operations relating to Permanent or Temporary Works, the same shall be repaired, replanted or otherwise corrected at Contractor's expense. All work areas shall be smoothened and graded in a manner to conform to natural appearance of the landscape as directed by the Employer's Representative. (b) All trees and shrubbery, which are not specifically required to be cleared or removed for construction purposes, shall be preserved and shall be protected from any damage that may be caused by Contractor's construction operations and equipment or by their employees/ workers. The removal of trees or shrubs will be permitted only after prior approval of the Employer's Representative. Special care shall be exercised where trees or shrubs are exposed to injuries by construction equipment, blasting, excavating, dumping, chemical damage or other operation and the Contractor shall adequately protect such trees by use of

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				such trees by use of protective barriers or other methods approved by the Employer's Representative. Trees shall not be used for anchorage. The Contractor shall be responsible for injuries to trees and shrubs caused by its operations and its employees/ workers. The terms "injury" shall include, without limitation, bruising, scarring, tearing and breaking of roots, trunks or branches. All injured trees and shrubs shall be restored as nearly practicable, without delay, to their original condition at the Contractor's expense. (c) Where trees have to be necessarily cut for progressing Temporary or Permanent Works, the Contractor shall arrange for compensatory afforestation as may be required by Environmental Rules and Regulations. (d) In the conduct of construction activities and operation of equipment, the Contractor shall utilise such practicable methods and devices as are reasonably available to control, prevent and otherwise minimize air/noise pollution. (e) Excessive emission of dust into the atmosphere will not be permitted during manufacture, handling and storage of concrete aggregates/ fly ash / earth/ building materials and the Contractor shall use such methods and equipment as are necessary for collection and disposal or prevention of dust during these operations. The Contractor's method of storing and handling cement shall also include means of eliminating atmospheric discharge of dust. Equipment and vehicles that give objectionable emission of exhaust gases shall not be operated. Burning of materials resulting from cleaning of trees, branches, combustible construction materials and rubbish may be permitted only when atmospheric conditions for burning are considered favourable. (f) Special care must be exercised in ensuring that the labour housed in labour camp within the Site area do not indulge in any activity like drinking alcohol, taking drugs, etc, and other activities that may affect the	protective barriers or other methods approved by the Employer's Representative. Trees shall not be used for anchorage. The Contractor shall be responsible for injuries to trees and shrubs caused by its operations and its employees/ workers. The terms "injury" shall include, without limitation, bruising, scarring, tearing and breaking of roots, trunks or branches. All injured trees and shrubs shall be restored as nearly practicable, without delay, to their original condition at the Contractor's expense. (c) Where trees have to be necessarily cut for progressing Temporary or Permanent Works, the Contractor shall arrange for compensatory afforestation as may be required by Environmental Rules and Regulations. (d) In the conduct of construction activities and operation of equipment, the Contractor shall utilise such practicable methods and devices as are reasonably available to control, prevent and otherwise minimize air/noise pollution. (e) Excessive emission of dust into the atmosphere will not be permitted during manufacture, handling and storage of concrete aggregates/fly ash / earth/ building materials and the Contractor shall use such methods and equipment as are necessary for collection and disposal or prevention of dust during these operations. The Contractor's method of storing and handling cement shall also include means of eliminating atmospheric discharge of dust. Equipment and vehicles that give objectionable emission of exhaust gases shall not be operated. Burning of materials resulting from cleaning of trees, branches, combustible construction materials and rubbish may be permitted only when atmospheric conditions for burning are considered favourable. (f) Special care must be exercised in ensuring that the labour housed in labour camp within the Site area do not indulge in any activity like drinking alcohol, taking drugs, etc, and other activities that may affect the ecological balance such as cutting of shrubs for fuel,

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
				ecological balance such as cutting of shrubs for fuel, creating open air nuisance etc. The Contractor shall not cut or destroy any tree in the campus to the maximum extent possible. In case any tree is to be cut he shall obtain prior permission from the competent authority under the relevant laws and shall plant equal number of saplings or adhere to the requirements of the prevailing Environmental laws / terms of the permission, whichever is more stringent. The Employer may assist the Contractor in obtaining such permission, including signing necessary documents. The Contractor shall use all means to minimize the effluents from its construction work and transportation activity or any other activity in the course of the execution of the Works. The Contractor shall take necessary steps for installation of grid connected roof-top solar photovoltaic systems of 50 KW capacity as per "Alo Shree" programme of the Government of West Bengal, in all the buildings forming part of the Project, to make the Project self-sustaining in utilization of power. The Contractor shall also make necessary provisions to ensure that the buildings constructed do fall under the category of Green buildings as per the applicable rules in the State of West Bengal and that the buildings are energy efficient as far as possible."	creating open air nuisance etc. The Contractor shall not cut or destroy any tree in the campus to the maximum extent possible. In case any tree is to be cut he shall obtain prior permission from the competent authority under the relevant laws and shall plant equal number of saplings or adhere to the requirements of the prevailing Environmental laws / terms of the permission, whichever is more stringent. The Employer may assist the Contractor in obtaining such permission, including signing necessary documents. The Contractor shall use all means to minimize the effluents from its construction work and transportation activity or any other activity in the course of the execution of the Works. The Contractor shall also make necessary provisions to ensure that the buildings constructed do fall under the category of Green buildings as per the applicable rules in the State of West Bengal and that the buildings are energy efficient as far as possible."
17	413	Section – 6 General Conditions of Contract ("GCC")	14.5	 "Except as otherwise stated in Sub-Clause 2.4 [Employer's Claims], the Employer shall pay to the Contractor: (a) the first tranche of Mobilisation Advance within 30 (thirty) days after the date of delivery of possession of 	 "Except as otherwise stated in Sub-Clause 2.4 [Employer's Claims], the Employer shall pay to the Contractor: (a) the Mobilisation Advance within 30 (thirty) days after the date of delivery of possession of the Site subject to Commencement of Works at the Site including setting up of site office etc. both for Contractor and the Employer (b) the amount which is due in respect of each Statement, other than the Final Statement, within 15 (fifteen) working days after receiving the Statement and supporting documents; and

SI. No.	Page No.	Section	Clause/ Sl. No.	Current Clause / Provision	Changed Clause / Provision
1					(c) the final amount due, within 60 (sixty) working days
1					after receiving the Final Statement and written
					discharge in accordance with Sub-Clause 14.9
				[Application for Final Payment] and Sub-Clause	[Application for Final Payment] and Sub-Clause 14.11
				14.11 [Discharge].	[Discharge].
				Payment of the amount due in INR shall be made into	Payment of the amount due in INR shall be made into
				any bank account, nominated by the Contractor."	any bank account, nominated by the Contractor."

General Manager, WBMSCL